

Junior Tip Cleaner

CLMS-B

This **automatic** cleaner improves thermal transfer of the tip in **only 1 second**, which means you save time and optimize production.

The operator just needs to **press the button** of the opening with the tool and two motorized brushes will clean the tip. It is also possible to select the **continuous mode**.

The **splashguard** helps keep the bench always clean and free of Foreign Object Debris (FOD).

The CLMS-B can be fitted into any work area thanks to its **reduced size** and it is very **easy to maintain**. The solder collector tray can be emptied and re-used with no wear and tear.



Specifications

Dimensions	91 x 95 x 114 mm (3.58 x 3.74 x 4.49 in)
Net weight	1,45 kg (3.20lb)
Brush diameter	34 mm
Brush speed	550 rpm 650 rpm (continuous mode)
AC Adapter	Input: 96 - 264 V, 50Hz Output: DC 12V , 1A
Package weight	1,63 kg (3.60lb) 1.452 kg (3.20 lb)


Product Packaging

Consumables [CLMS-A8](#)

Connectables

Brushes for CLMS
CLMS-A8



 **Documentation**

- VideoTutorial CLMS Tutorial
- VideoTutorial How to change the CLMS Gate protector?

- Manuals CLMS Junior Tip Cleaner Manual